
PRO SLIMPAR

DMX Channel



DMXコントロールモード

DMX 3 channel

channel	value	function
1	0 - 255	Hue
2	0 - 255	Saturation
3	0 - 255	Value(brightness)

DMX 4 channel

channel	value	function
1	0 - 255	Red Dimmer
2	0 - 255	Green Dimmer
3	0 - 255	Blue Dimmer
4	0 - 255	White Dimmer

DMX 6 channel

channel	value	function
1	0 - 255	0 = Off 1 - 255 = Master dimmer
2	0-9	No function
	10-255	Strobe from min to max
3	0 - 255	Red Dimmer
4	0 - 255	Green Dimmer
5	0 - 255	Blue Dimmer
6	0 - 255	White Dimmer

DMX 10 channel

channel	value	function
1	0 - 255	0 = Off 1 - 255 = Master dimmer
2	0 - 9	No function
	10 - 255	Strobe from min to max
3	0 - 255	Red Dimmer
4	0 - 255	Green Dimmer
5	0 - 255	Blue Dimmer
6	0 - 255	White Dimmer
7	0 - 10	No function
	11 - 20	R100%/Gup/B0%/W0%
	21 - 30	Rdown/G100%/B0%/W0%
	31 - 40	R0%/G100%/Bup/W0%
	41 - 50	Rup/Gdown/B100%/W0%
	51 - 60	Rup/G0%/B100%/W0%
	61 - 70	R100%G0%Bdown/W0%
	71 - 80	R100%/G0%/B0%/Wup
	81 - 90	R100%/G0%/B0%/Wdown
	91 - 100	R↑/G↓/B0%/W0%→R↓G↑/B0%/W0%
	101 - 110	R↑/G0%/B↓/W0%→R↓/G0%B↑/W0%
	111 - 120	R0%/G↑/B↓/W0%→R0%/G↓/B↑/W0%
	121 - 130	R↑/G↑/B↓/W0%→R↓/G↓/B↑/W0%
	131 - 140	R↑/G↓/B↓/W0%→R↓/G↑/B↑/W0%
	141 - 150	R↑/G↓/B↑/W0%→R↓/G↑/B↓/W0%
	151 - 160	R↑/G0%/B↓/W0%→R↓/G↑/B0%/W0%→R0%/G↓/B↑/W0%
	161 - 170	R↑/G100%/B↓/W0%→R100%/G↓/B↑/W0%→R↓/G↑/B100%/W0%R↓/G↑/B0%/W0%→R0%/G↓/B↑/W0%→R0%G0%/B↓/W↑
	171 - 180	R↑/G0%/B0%/W↓ R0%/G100%/B↓/W0%→R↑/G100%B0%/W0%
	181 - 190	R100%/G↓/B0%/W0%→R100%/G0%/B↑/W0%→ R↓/G0%/B100%/W0%→R0%/G↑/B100%/W0%
	191 - 200	RGBW
	201 - 205	White 1
	206 - 210	White 2
	211 - 215	White 3
	216 - 220	White 4
	221 - 225	White 5
	226 - 230	White 6
	231 - 235	White 7
	236 - 240	White 8
241 - 245	White 9	
246 - 250	White 10	
251 - 255	White 11	
8	0 - 7	Default
	8 - 17	Auto 1
	18 - 27	Auto 2
	28 - 37	Auto 3
	38 - 47	Auto 4
	48 - 57	Auto 5
	58 - 67	Auto 6
	68 - 77	Auto 7
	78 - 87	Auto 8
	88 - 97	Auto 9
	98 - 107	Auto 10
	108 - 117	Custom1
	118 - 127	Custom2
	128 - 137	Custom3
	138 - 147	Custom4
	148 - 157	Custom5
	158 - 167	Custom6
	168 - 177	Custom7
178 - 187	Custom8	
188 - 197	Custom9	
198 - 207	Custom10	
208 - 255	Custom11	
9	0 - 255	Speed when auto is enable
	00 255	Id address set